## HAY-DC-M

The HAY-DC-M is a Plug and play power meter, it is designed to test voltage and current of a CCTV Camera.

## **Specification**

Input Voltage: 5 - 35V

Input Current: 0.01-7.00Amp

Test Accuracy: Voltage ± 1%, Current ± 1%

Power consumption: <25mA

Input/Output interface: 2.1mm DC Socket and plug

Size: 85 x 41 x 22.3mm

Weight:50gram Warranty: 3 Years



Fig 1



Fig 2



Fig 1 Shows camera current and voltage in normal mode

Fig 2 Shows camera current and voltage where IR is activated on camera

## Connections

Connect from power source to DC IN Socket, then insert the meter's DC plug to the Camera DC Socket. Voltage and Current of the Powered Device e.g. Camera will show on the meter.

